

Manual Call Point

The manual Call Point is compatible to Fire Alarm Panels, it has got twin RED LEDs as Visual Indication.

This will be Mounted in corridors and Lobby's in High-rise Building.

Product Specifications

- Designed as per IS 2189: 1988
- Push switch along with dual Red LED for Alarm indication
- Built with hammer and chain
- Available in Red & White color
- Glass area more than 40 square centimeters



Technical Specifications

Operating Voltage	24 V DC
Power Requirement	< 5 mA Normal 20 mA Maximum
Bottom Box Dimension	H-70 mm, W-100 mm, D-40 mm
Front Plate Dimension	H-90 mm, W-120 mm, D-12 mm
Model Number	RE-540

Royale Electronics

No 76 Southend Road, Basavanagudi Bangalore 560004

Phone: +91-080-26500340, +91-080-26676824

Hand Phone: +919880411995, +919945211995

e- Mail royaleelectronics1995@gmail.com

Reliable, Robust & Royale